

auto electrical parts

Technical Information Sheet

Part No. 0-728-20


12 volt 20/30 amp make and break 6RA type relay. 5 \times 6.3mm terminals, neoprene sealed. Replace SRB131, 143, 146.

Additional information


To replace SRB131 leave terminal C1 unconnected.



Technical Drawing (not to scale)



Circuit Diagram



Specification

Type Change over relay

Voltage 12 volt

Current 30/40 amp maximum (resitive load at 14 volt dc)

Coil current 0.12 amp (nominal)

Terminals 6.3mm blade
Contacts Silver alloy
Operating temperature -40° to +85°C
Humidity 20 to 85% RH
Dimensions See diagram

Weight 95g

The information contained in this document is correct to the best of our knowledge at the time of printing. However, specifications may change at any time without notice.